



Commercial, Industrial  
and Residential Electrical Products



**NEW!**  
IMPROVED



# Save Time and Effort! Push-in Cable Connectors



38RAC



40RAC



## Rugged one-piece design provides fast tool-free install!

### Applications

RACO's new *Push-in* cable connectors make it easy to secure metal-clad cable into boxes or enclosures. Simply insert a cable into the cable opening, then snap the box end of the connector into a box knockout, done! No tools needed for a secure assembly. *Push-in* connectors are perfect for new or old work and can be removed and reused.

### Features

- Fits standard 1/2" knockouts in electrical boxes or enclosures
- Both connectors designed to terminate MC-PCS, MCI, MCI-A, AC, HCF, and FMC
- 40RAC tinted blue inside to indicate larger cable range
- Die-cast zinc construction with nylon anti-short bushing
- For use in dry locations
- See back for cable size ranges



| Catalog No. | Description                      | Unit Carton Qty. | Inner Carton Qty. | Ship Carton Qty. | Carton 1 of 5  |
|-------------|----------------------------------|------------------|-------------------|------------------|----------------|
| 38RAC       | 3/8" Push-in Connector (1/2" KO) | 50               | 30050160000381    | 500              | 50050169000385 |
| 40RAC       | 3/8" Push-in Connector (1/2" KO) | 50               | 30050169000404    | 500              | 50050169000408 |

**38RAC**

| CABLE TYPE (Steel & Aluminum) | CABLE RANGES  |
|-------------------------------|---|
| MC                            | 14/2 - 10/3   |
| MCI-A                         |   |
| AC/HCF                        |   |
| MCI-A HCF                     | 12/2 - 10/3   |
| MC-PCS (SOLID)                | 12/2 - 12/3   |
| RWFMC CONDUIT                 | <b>3/8" TRADE SIZE FLEX<br/>Anti Short Bushing Required</b> |

Cable Diameter Range: 0.402" - 0.610"

**40RAC**

| CABLE TYPE (Steel & Aluminum) | CABLE RANGES  |
|-------------------------------|---|
| MC                            | 14/3 - 10/3   |
| MCI-A                         |   |
| AC                            |   |
| AC HCF                        | 14/2 - 10/3   |
| MCI-A HCF                     | 12/2 - 10/3   |
| MC-PCS (SOLID)                | 12/2 - 12/3   |
| RWFMC CONDUIT                 | <b>3/8" TRADE SIZE FLEX<br/>Anti Short Bushing Required</b> |

Cable Diameter Range: 0.470" - 0.610"

**38RAC/40RAC CONNECTOR REMOVAL INSTRUCTIONS**

